

Nord Electro 5 Comparison Chart

	NORD ELECTRO 5			NORD ELECTRO 4		
Hardware	Electro 5 HP	Electro 5D 73	Electro 5D 61	Electro 4 HP	Electro 4 SW73	Electro 4D SW61
Keybed	73-key Hammer Action Portable	73-key Semi-weighted Waterfall	61-key Semi-weighted Waterfall	73-key Hammer Action Portable	73-key Semi-weighted Waterfall	61-key Semi-weighted Waterfall
Display	128x64 OLED display			7-segment LED		
Outputs	2 outputs (1 stereo or 2 mono)			2 outputs (1 stereo or 2 mono)		
Control Pedal input	yes			yes		
Monitor input	yes			yes		
Drawbars	Digital LED	Physical		Digital LED	Digital LED	Physical
	Electro 5 HP	Electro 5D 73	Electro 5D 61	Electro 4 HP	Electro 4 SW73	Electro 4D SW61
Layer	Organ+Piano, Organ+Synth or Synth+Piano			no		
Split	6 Split points			no		
Programs	Program Mode (8 banks x 50 programs), Live Mode and Set List Mode			4 program buttons x 32 pages (128 locations)		
Live/auto save programs	3 locations			4 locations		
MIDI over USB	yes			yes		
Sound Manager 6.x	Extended features			Extended features		
Organ Section	Electro 5 HP	Electro 5D 73	Electro 5D 61	Electro 4 HP	Electro 4 SW73	Electro 4D SW61
Organ polyphony	Full			Full		

Organ models	C2D B3 Simulation, Farfisa, Vox and Principal Pipe			C2D B3 Simulation, Farfisa, Vox		
Rotary speaker simulation	C2D 122 Rotary Speaker simulation			122 Rotary speaker simulation		
Mount for Half-Moon Switch	no	yes		no		
Piano Section	Electro 5 HP	Electro 5D 73	Electro 5D 61	Electro 4 HP	Electro 4 SW73	Electro 4D SW61
Nord Piano Library memory	1GB			380MB	380MB	180MB
Piano polyphony	40/60 (stereo/mono)			40/60 (stereo/mono)		
Advanced String Resonance (Gen 2)	yes			no		
Long Release	yes			yes		
Dynamic Curves	yes			yes		
Samples Section	Electro 5 HP	Electro 5D 73	Electro 5D 61	Electro 4 HP	Electro 4 SW73	Electro 4D SW61
Nord Sample Library memory	256MB			128MB		68MB
Sample polyphony	15 voices			15 voices		
Velocity Control	Yes, 3 modes (Filter and Amplitude)			On/Off		
Envelope Control	Attack, Decay/Release controls			Release 1/2		
Effects Section	Electro 5 HP	Electro 5D 73	Electro 5D 61	Electro 4 HP	Electro 4 SW73	Electro 4D SW61
Effect 1	Tremolo, Pan, Wah, Ring Modulator All are Control Pedal controllable			Pan, Tremolo, Autowah, Pedal Wah, Ring Modulator		

Effect 2	Phaser, Flanger, Chorus, Vibe Deep mode available for each effect			Phaser, Flanger, Chorus		
Delay	yes			x (shared with Reverb)		
Eq	3 Band, mid sweep			3 Band, mid sweep		
Amp Simulation/ Compressor	Twin, JC, Small, Compressor, C2D 122 Rotary, Tube Overdrive			Twin, JC, Small, 122 Rotary, Compressor		
Reverb	5 modes (Room, Stage, Hall, Stage soft, Hall soft)			5 modes (Room, Stage, Hall, Stage soft, Hall soft) (when not using delay)		
Dimensions	Electro 5 HP	Electro 5D 73	Electro 5D 61	Electro 4 HP	Electro 4 SW73	Electro 4D SW61
Weight	11.4 kg / 25.13 lbs	9.2 kg / 20.28 lbs	8.1 kg / 17.85 lbs	11 kg / 24.25 lbs	9.1 kg / 18.2 lbs	7.65 kg / 15.3 lbs
Width	1074 mm / 42.3"	1066 mm / 42"	900 mm / 35.4"	1078 mm / 42.4"	1120 mm / 44.1"	900 mm / 35.4"
Depth	344 mm / 13.5"	296 mm / 11.7"	296 mm / 11.8"	344 mm / 13.5"	300 mm / 11.8"	300 mm / 11.8"
Height	121 mm / 4.8"	97 mm / 3.8"	97 mm / 3.8"	121 mm / 4.8"	100 mm / 3.9"	100 mm / 3.9"